



## SCUBA RGBW



### DESCRIPTION:

SCUBA RGBW horizontal bend series constructed using Silicon extrusion process. Uniform, dot free light emission, good appearance consistency. Anti-yellowing, high temperature and corrosion resistance, weak acid and alkali resistance UV proof for true outdoor applications. Easy installation with clips and bendable track. Cuttable for Flexible application.

Control mode : DALI, DMX

### TECHNICAL DETAILS:

Power : 12W/M  
 Voltage : DC24V  
 CRI >90  
 Glare Rating : UGR<19  
 Length/Reel : 5M/10M  
 Cutting length : 100mm  
 Led Qty : 84LEDs/M  
 Led Driver: Vossloh Schwabe  
 Working Temperature : -20~45°C  
 Storage Temperature : -30~80°C  
 Voltage Range : 23~25V dc  
 Reverse Voltage : 25V dc  
 Warranty : 5 years


### LUMENS PER METER:

CCT	12W
RGBW/2700K	552lm
RGBW/3000K	558lm
RGBW/3500K	564lm
RGBW/4000K	570lm
RGBW/5000K	576lm


### INSTALLATION : Horizontal Bend

Product Code : 8721515


### DIMENSION:




### LIGHT DISTRIBUTION:




### End cap



### BENDING:



### Wire at end



### Standards

EN 60598-1


EN 60598-2-2

EN 60598-3-2


Order Code Ex : 8721515  
 Product Code 8721515  
 Power 12W  
 CCT 82  
 12-12W | 82 RGBW

Pluxb luminaires are developed with globally recognized and tested components suppliers, however as per international standards tolerance in initial flux and connected load is at ±5%. Unless stated otherwise, the values apply to an ambient temperature of 25°C

## ACCESSORIES



Aluminium Profile  
Order Code : 8721515-01  
Dimension : L1000\*W20.5\*H17.6mm  
Material : aluminium  
Color : silver



End Cap 5PIN  
Order Code : 8721515-06  
Color : white  
Cable entry : front/side/bottom  
Picture : front



Curved Profile  
Order Code : 8721515-02  
Dimension : L500\*W17\*H15mm  
Material : stainless steel  
Color : silver



Closed End Cap  
Order Code : 8721515-07  
Material : silicone  
Color : white



Mounting Clips  
Order Code : 8721515-03  
Dimension : L20\*W16.6\*H12.4mm  
Material : stainless steel  
Color : silver  
Each meter led strips needs  
2 clips + 2 screws



IP67 T Type Connector  
Order Code : 8721515-08  
Wire Gauge : 0.326mm<sup>2</sup>/22AWG  
Protection : IP67 (Mated)



IP67 Connector 5PIN  
Order Code : 8721515-04  
Wire gauge : 0.326mm<sup>2</sup>/22AWG  
Protection : IP67 (Mated)  
Connector type : Male




Scissor  
Order Code : 8721515-09




IP67 Connector 5PIN  
Order Code : 8721515-05  
Wire gauge : 0.326mm<sup>2</sup>/22AWG  
Protection : IP67 (Mated)  
Connector type : Female

## ADDITIONAL INFO



- ▶ Please light it up for a quick check before installation.
- ▶ Bending diameter of SCUBA RGBW 1515 is 300mm, do not bend to Top direction, or bend too sharp or twist. If bend it wrongly, PCB inside will be damaged and the lighting fixture will not turn on.
- ▶ During installation, please make sure there are at least two workers to cooperate together and strictly follow the instruction manuals.
- ▶ product itself for 5 years from the date of purchase. This warranty does not cover failures due to abuse, misuse, improper handling, act of nature, negligence, normal wear, accidental damage, repairs made by the purchaser or incorrect voltage conditions.




**Note:**

-12W/M Max. 10mtr run length to single side feed.


-The given data are typical values due to the tolerances of the production process and the electrical components, values for light output and electrical power can vary up to 5%.

# WIRING DIAGRAM


## DMX



## 1. DALI



## 2. WITH PUSH DIM




## GENERAL MOUNTING


LED neon flex can be fastened to surfaces using appropriate accessories available from distributor. Please refer to data sheets or contact technical support for a copy. The use of glues and resins as fixing agents should be avoided. Use of glues and resins may invalidate the warranty of the product unless its use is agreed in writing by distributor as part of a detailed project specification.

The images indicate one type of fixing available in the accessories range. The different fixings serve obvious purposes, however when in doubt technical support should be contacted.



Quantities of accessories and fixings are dependent on the type and its effect on the variant it's being used with. Care should be taken to ensure drooping is avoided, and to ensure that is fastened adequately to avoid stresses on itself.





Press the flex light into mounted aluminum channel in one direction.






Incorrect installation like below picture could lead to light failure.




Ensure the feeding cable not bear force, keep the head 10mm in natural loose. ← →



Mount the cable junction in hermetic enclosure like waterproof junction box in outdoor application.




Do not bend against light terminals; otherwise it will lead to failure of connector waterproof.




# INSTALLATION

## Attention





1. Correct bending way.



## Installation





1. During LED strip installation, ensure to uncoil the strip loop by loop and maintain perpendicular alignment with the mounting profile. Avoid twisting or knoting of the strip at all times.




2. Align the LED strip with the opening of the profile, gently lift and press the strip into the profile, and strictly avoid excessive bending or lifting of the strip.



3. Align the LED strip with the opening of the profile, gently lift and press the strip into the profile, and strictly avoid excessive bending or lifting of the strip.




The safe tensile force for the LED strip shall be  $\leq 4\text{ON}$   
Excessive force may damage the internal circuitry.




The safe twisting angle for the LED strip shall not exceed 180°.


## Warning sign




Cuttable Marking Area  
(on the bottom or side of the product).




Neat and smooth cut.




Mount the roll on a rod over the box and rotate to use.




Top Bend.




Side Bend.




Free Bend.




Do not leave uneven cuts.




Do not twist during use.




Repeated bending may damage electronic circuits.



Do not puncture or scratch with sharp objects.



Do not bend at sharp angles.



Do not jerk or yank when using the product.

1. The cutting marks are located on the PCB. Refer to the product cutting line window or laser markings on the surface to identify the trimming position.
2. During transportation and application, please observe the above warning labels. Proper handling ensures optimal performance and user satisfaction.